1   TITLE OF THE INVENTION
        MICROPHONE ARRAY APPARATUS

    BACKGROUND THE INVENTION

5   1. Field of the Invention
            The present invention relates to a
    microphone array apparatus which has an array of
    microphones in order to detect the position of a sound
    source, emphasize a target sound and suppress noise.

10   The microphone array apparatus has an array
    of a plurality of omnidirectional microphones and
    equivalently define a directivity by emphasizing a
    target sound and suppressing noise. Further, the
    microphone array apparatus is capable of detecting the

15 position of a sound source on the basis of a
    relationship among the phases of output signals of the
    microphones. Hence, the microphone array apparatus
    can be applied to a video conference system in which a
    video camera is automatically oriented towards a

20 speaker and a speech signal and a video signal can
    concurrently be transmitted. In addition, the speech
    of the speaker can be clarified by suppressing ambient
    noise. The speech of the speaker can be emphasized by
    adding the phases of speech components. It is now

25 required that the microphone array apparatus can
    stably operate.
            If the microphone array apparatus is
    directed to suppressing noise, filters are connected
    to respective microphones and filter coefficients are

30 adaptively or fixedly set so as to minimize noise
    components (see, for example, Japanese Laid-Open
    Patent Application No. 5-111090). If the microphone
    array apparatus is directed to detecting the position
    of a sound source, the relationship among the phases

35 of the output signals of the microphones is detected,
    and the distance to the sound source is detected (see,
    for example, Japanese Laid-Open Patent Application

1   Nos. 63-177087 and 4-236385).

An echo canceller is known as a device which
utilizes the noise suppressing technique.   For
example, as shown in Fig. 1, a transmit/receive
5   interface 202 of a telephone set is connected to a
network 203.   An echo canceller is connected between a
microphone 204 and a speaker 205.   A speech of a
speaker is input to the microphone 204.   A speech of a
speaker on the other (remote) side is reproduced
10   through the speaker 205.   Hence, a mutual
communication can take place.

A speech transferred from the speaker 205 to
the microphone 204, as indicated by a dotted line
shown in Fig. 1 forms an echo (noise) to the other-
15   side telephone set.   Hence, the echo canceller 201 is
provided that includes a subtracter 206, an echo
component generator 207 and a coefficient calculator
208.   Generally, the echo generator 207 has a filter
structure which produces an echo component from the
20   signal which drives the speaker 205.   The subtracter
206 subtracts the echo component from the signal from
the microphone 204.   The coefficient calculator 208
controls the echo generator 207 to update the filter
coefficients so that the residual signal from the
25   subtracter 206 is minimized.

The updating of the filter coefficients c1,
c2, ..., cr of the echo component generator 207 having
the filter structure can be obtained by a known
maximum drop method.   For example, the following
30   evaluation function J is defined based on an output
signal e (the residual signal in which the echo
component has been subtracted) of the subtracter 206:

$$J = e^2 \tag{1}$$

35

According to the above evaluation function, the filter
coefficients c1, c2, ..., cr are updated as follows:

$$\begin{bmatrix} c1 \\ c2 \\ \cdot \\ \cdot \\ cr \end{bmatrix} = \begin{bmatrix} c1_{old} \\ c2_{old} \\ \cdot \\ \cdot \\ cr_{old} \end{bmatrix} + \alpha * (e/f_{norm}) * \begin{bmatrix} f(1) \\ f(2) \\ \cdot \\ \cdot \\ f(r) \end{bmatrix} \qquad (2)$$

where $0.0 < \alpha < 0.5$

$$f_{norm} = (f(1)^2 + f(2)^2 + \cdots f(r)^2)^{1/2} \qquad (3)$$

In the above expressions, a symbol "*" denotes multiplication, and "r" denotes the filter order. Further, $f(1)$, $\cdots$, $f(r)$ respectively denote the values of a memory (delay unit) of the filter (in other words, the output signals of delay units each of which delays the respective input signal by a sample unit). A symbol "f_{norm}" is defined as equation (3), and a symbol "α" is a constant, which represents the speed and precision of convergence of the filter coefficients towards the optimal values.

The echo canceller 201 has filter orders as many as 100. Hence, another echo canceller using a microphone array as shown in Fig. 2 is known. There are provided an echo canceller 211, a transmit/receive interface 212, microphones 214-1 - 214-n forming a microphone array, a speaker 215, a subtracter 216, filters 217-1 - 217-n, and a filter coefficient calculator 218.

In the structure shown in Fig. 2, acoustic components from the speaker 215 to the microphones 214-1 - 214-n are propagated along routes indicated by broken lines and serve as echoes. Hence, the speaker 215 is a noise source. The updating control of the filter coefficients c11, c12, ..., c1r, ..., cn1, cn2, ..., cnr in the case where the speaker does not make any speech is expressed by using the evaluation function (1) as follows:

- 4 -

1

$$\begin{bmatrix} c11 \\ c12 \\ \vdots \\ c1r \end{bmatrix} = \begin{bmatrix} c11_{old} \\ c12_{old} \\ \vdots \\ c1r_{old} \end{bmatrix} - \alpha * (e / f1_{norm}) * \begin{bmatrix} f1(1) \\ f1(2) \\ \vdots \\ f1(r) \end{bmatrix}$$

5
$$\cdots (4)$$

$$\begin{bmatrix} cp1 \\ cp2 \\ \vdots \\ cpr \end{bmatrix} = \begin{bmatrix} cp1_{old} \\ cp2_{old} \\ \vdots \\ cpr_{old} \end{bmatrix} + \alpha * (e / fp_{norm}) * \begin{bmatrix} fp(1) \\ fp(2) \\ \vdots \\ fp(r) \end{bmatrix}$$

10

where p = 2, 3, ..., n   (5)

The equation (4) relates to a case where
15   one of the microphones 214-1 - 214-n, for example, the
microphone 214-1 is defined as a reference microphone,
and indicates the filter coefficients c11, c12, ...,
c1r of the filter 217-1 which receives the output
signal of the above reference microphone 214-1. The
20   equation (5) relates to the microphones 214-2 - 214-n
other than the reference microphones, and indicates
the filter coefficients c21, c22, ..., c2r, ..., cn1,
cn2, ..., cnr. The subtracter 216 subtracts the
output signals 217-2 - 217-n of the microphones 214-2
25   - 214-n from the output signal 217-1 of the reference
microphone 214-1.

Fig. 3 is a block diagram for explaining a
conventional process of detecting the position of a
sound source and emphasizing a target sound. The
30   structure shown in Fig. 3 includes a target sound
emphasizing unit 221, a sound source detecting unit
222, delay units 223 and 224, a number-of-delayed-
samples calculator 225, an adder 226, a
crosscorrelation coefficient calculator 227, a
35   position detection processing unit 228 and microphones
229-1 and 229-2.

The target sound emphasizing unit 221

1   includes the delay units 223 and 224 of z^{-da} and z^{-db},
    the number-of-delayed-samples calculator 225 and the
    adder 226. The sound source position detecting unit
    222 includes the crosscorrelation coefficient
5   calculator 227 and the position detection processing
    unit 228. The number-of-delayed samples calculator
    225 is controlled by the following factors. The
    crosscorrelation coefficient calculator 227 of the
    sound source position detecting unit 222 obtains a
10 crosscorrelation coefficient r(i) of output signals
    a(j) and b(j) of the microphones 229-1 and 229-2. The
    position detection processing unit 228 obtains the
    sound source position by referring to a value of i,
    imax, at which the maximum of the crosscorrelation
15 coefficient r(i) can be obtained.

    The crosscorrelation coefficient r(i) is
    expressed as follows:

$$r(i) = \Sigma^{n}_{j=1} a(j) * b(j+i) \qquad\qquad (6)$$

20
    where $\Sigma^{n}_{j=1}$ denotes a summation of j=1 to j=n, and i
    has a relationship $-m \leq i \leq m$. The symbol "m" is a
    value dependent on the distance between the
    microphones 229-1 and 229-2 and the sampling
25 frequency, and is written as follows:

$$m = [(\text{sampling frequency}) * (\text{intermichrophone}$$
$$\text{distance})]/(\text{speed of sound}) \qquad (7)$$

30 where n is the number of samples for a convolutional
    operation.
    The number of delayed samples da of the z^{-da}
    delay unit 223 and the number of delayed samples db of
    the z^{-db} delay unit 224 can be obtained as follows
35 from the value imax at which the maximum value of the
    crosscorrelation coefficient r(i) can be obtained:

where $i \geq 0$, da = i, db = 0
where $i < 0$, da = 0, db = -i.

Hence, the phases of the target sound from the sound source are made to coincide with each other and are added by the adder 226. Hence, the target sound can be emphasized.

However, the above-mentioned conventional microphone array apparatus has the following disadvantages.

In the conventional structure directed to suppressing noise, when the speaker of the target sound source does not speak, the echo components from the speaker to the microphone array can be canceled by the echo canceller. However, when a speech of the speaker and the reproduced sound from the speaker are concurrently input to the microphone array, the updating of the filter coefficients for canceling the echo components (noise components) does not converge. That is, the residual signal e in the equations (4) and (5) corresponds to the sum of the components which cannot be suppressed by the subtracter 216 and the speech of the speaker. Hence, if the filter coefficients are updated so that the residual signal e is minimized, the speech of the speaker which is the target sound is suppressed along with the echo components (noise). Hence, the target noise cannot be suppressed.

In the conventional structure directed to detecting the sound source position and emphasizing the target sound, the output signals a(j) and b(j) of the microphones 229-1 and 229-2 shown in Fig. 3 generally have an autocorrelation in the vicinity of the sampled values. If the sound source is white noise or pulse noise, the autocorrelation is reduced, while the autocorrelation for vice is increased. The crosscorrelation function r(i) defined in the equation

1   (6) has a less variation as a function of i with respect to a signal having comparatively large autocorrelation than a variation with respect to a signal having comparatively small autocorrelation.

5   Hence, it is very difficult to obtain the correct maximum value and precisely and rapidly detect the position of the sound source.

    In the conventional structure directed to emphasizing the target sound so that the phases of the

10   target sounds are synchronized, the degree of emphasis depends on the number of microphones forming the microphone array. If there is a small crosscorrelation between the target sound and noise, the use of N microphones emphasizes the target sound

15   so that the power ratio is as large as N times. If there is a large correction between the target sound and noise, the power ratio is small. Hence, in order to emphasize the target sound which has a large crosscorrelation to the noise, it is required to use a

20   large number of microphones. This leads to an increase in the size of the microphone array. It is very difficult to identify, under noisy environment, the position of the power source by utilizing the crosscorrelation coefficient value of the equation

25   (6).

SUMMARY OF THE INVENTION

    It is a general object of the present invention to provide a microphone array apparatus in

30   which the above disadvantages are eliminated.

    A more specific object of the present invention is to provide a microphone array apparatus capable of stably and precisely suppressing noise, emphasizing a target sound and identifying the

35   position of a sound source.

    The above objects of the present invention are achieved by a microphone array apparatus

1   comprising: a microphone array including microphones
(which correspond to parts indicated by reference
numbers 1-1 - 1-n in the following description), one
of the microphones being a reference microphone (1-1);
5   filters (2-1 - 2-n) receiving output signals of the
microphones; and a filter coefficient calculator (4)
which receives the output signals of the microphones,
a noise and a residual signal obtained by subtracting
filtered output signals of the microphones other than
10   the reference microphone from a filtered output signal
of the reference microphone and which obtain filter
coefficients of the filters in accordance with an
evaluation function based on the residual signal.
With this structure, even when speech of a speaker
15   corresponding to the sound source and the noise are
concurrently applied to the microphones, the
crosscorrelation function value is reduced so that the
noise can be effectively suppressed and the filter
coefficients can continuously be updated.
20   The above microphone array apparatus may be
configured so that it further comprises: delay units
(8-1 - 8-n) provided in front of the filters; and a
delay calculator (9) which calculates amounts of
delays of the delay units on the basis of a maximum
25   value of a crosscorrelation function of the output
signals of the microphones and the noise. Hence, the
filter coefficients can easily be updated.
         The microphone array apparatus may be
configured so that the noise is a signal which drives
30   a speaker. This structure is suitable for a system
that has a speaker in addition to the microphones. A
reproduced sound from the speaker may serve as noise.
By handling the speaker as a noise source, the signal
driving the speaker can be handled as the noise, and
35   thus the filter coefficients can easily be updated.
         The microphone array apparatus may further
comprise a supplementary microphone (21) which outputs

the noise.   This structure is suitable for a system
which has microphones but does not have a speaker.
The output signal of the supplementary microphone can
be used as the noise.

The microphone array apparatus may be
configured so that the filter coefficient calculator
includes a cyclic type low-pass filter (Fig. 10) which
applies a comparatively small weight to memory values
of a filter portion which executes a convolutional
operation in an updating process of the filter
coefficients.

The above objects of the present invention
are also achieved by a microphone array apparatus
comprising: a microphone array including microphones
(51-1, 51-2); linear predictive filters (52-1, 52-2)
receiving output signals of the microphones; linear
predictive analysis units (53-1, 53-2) which receives
the output signals of the microphones and update
filter coefficients of the linear predictive filters
in accordance with a linear predictive analysis; and a
sound source position detector (54) which obtains a
crosscorrelation coefficient value based on linear
predictive residuals of the linear predictive filters
and outputs information concerning the position of a
sound source based on a value which maximizes the
crosscorrelation coefficient.   Hence, even when speech
of a speaker corresponding to the sound source and the
noise are concurrently applied to the microphones,
autocorrelation function values of samples about the
speech signal are reduced to the linear predictive
analysis, so that the position of the target source
can accurately be detected.   Thus, speech from the
target sound can be emphasized and noise components
other than the target sound can be suppressed.

The microphone array apparatus may be
configured so that: a target sound source is a
speaker; and the linear predictive analysis unit

1   updates the filter coefficients of the linear
predictive filters by using a signal which drives the
speaker. Hence, the linear predictive analysis unit
can be commonly used to the linear predictive filters
5   corresponding to the microphones.

       The above-mentioned objects of the present
invention are achieved by a microphone array apparatus
comprising: a microphone array including microphones
(61-1, 61-2); a signal estimator (62) which estimates
10   positions of estimated microphones in accordance with
intervals at which the microphones are arranged by
using the output signals of the microphones and a
velocity of sound and which outputs output signals of
the estimated microphones together with the output
15   signals of the microphones forming the microphone
array; and a synchronous adder (63) which pulls phases
of the output signals of the microphones and the
estimated microphones and then adds the output
signals. Hence, even if a small number of microphones
20   is used to form an array, the target sound can be
emphasized and the position of the target sound source
can precisely be detected as if a large number of
microphones is used.

       The microphone array apparatus may further
25   comprise a reference microphone (71) located on an
imaginary line connecting the microphones forming the
microphone array and arranged at intervals at which
the microphones forming the microphone array are
arranged, wherein the signal estimator which corrects
30   the estimated positions of the estimated microphones
and the output signals thereof on the basis of the
output signals of the microphones forming the
microphone array.

       The microphone array apparatus may further
35   comprise an estimation coefficient decision unit (74)
weights an error signal which corresponds to a
difference between the output signal of the reference

1   microphone and the output signals of the signal
estimator in accordance with an acoustic sense
characteristic so that the signal estimator performs a
signal estimating operation on a band having a

5   comparatively high acoustic sense with a comparatively
high precision.

          The microphone array apparatus may be
configured so that: given angles are defined which
indicate directions of a sound source with respect to

10   the microphones forming the microphone array; the
signal estimator includes parts which are respectively
provided to the given angles; the synchronous adder
includes parts which are respectively provided to the
given angles; and the microphone array apparatus

15   further comprises a sound source position detector
which outputs information concerning the position of a
sound source based on a maximum value among the output
signals of the parts of the synchronous adder.

          The above objects of the present invention

20   are also achieved by a microphone array apparatus
comprising: a microphone array including microphones
(91-1, 91-2); a sound source position detector (92)
which detects a position of a sound source on the
basis of output signals of the microphones; a camera

25   (90) generating an image of the sound source; a second
detector (93) which detects the position of the sound
source on the basis of the image from the camera; and
a joint decision processing unit (94) which outputs
information indicating the position of the sound

30   source on the basis of the information from the sound
source position detector and the information from the
second detector. Hence, the position of the target
sound source can by rapidly and precisely detected.

35   BRIEF DESCRIPTION OF THE DRAWINGS

          Other objects, features and advantages of
the present invention will become more apparent from

the following detailed description when read in
conjunction with the accompanying drawings, in which:

Fig. 1 is a block diagram of a conventional
echo canceller;

Fig. 2 is a diagram of a conventional echo
canceller using a microphone array;

Fig. 3 is a block diagram of a structure
directed to detecting the position of a sound source
and emphasizing the target sound;

Fig. 4 is a block diagram of a first
embodiment of the present invention;

Fig. 5 is a block diagram of a filter which
can be used in the first embodiment of the present
invention;

Fig. 6 is a block diagram of a second
embodiment of the present invention;

Fig. 7 is a flowchart of an operation of a
delay calculator used in the second embodiment of the
present invention;

Fig. 8 is a block diagram of a third
embodiment of the present invention;

Fig. 9 is a block diagram of a fourth
embodiment of the present invention;

Fig. 10 is a block diagram of a low-pass
filter used in a filter coefficient updating process
executed in the embodiments of the present invention;

Fig. 11 is a block diagram of a structure
using a digital signal processor (DSP);

Fig. 12 is a block diagram of an internal
structure of the DSP shown in Fig. 11;

Fig. 13 is a block diagram of a delay unit;

Fig. 14 is a block diagram of a fifth
embodiment of the present invention;

Fig. 15 is a block diagram of a detailed
structure of the fifth embodiment of the present
invention;

Fig. 16 is a diagram showing a relationship

1   between the sound source position and imax;

Fig. 17 is a block diagram of a sixth
embodiment of the present invention;

Fig. 18 is a block diagram of a seventh
5   embodiment of the present invention;

Fig. 19 is a block diagram of a detailed
structure of the seventh embodiment of the present
invention;

Fig. 20 is a block diagram of an eighth
10   embodiment of the present invention;

Fig. 21 is a block diagram of a ninth
embodiment of the present invention; and

Fig. 22 is a block diagram of a tenth
embodiment of the present invention.

15

DESCRIPTION OF THE PREFERRED EMBODIMENTS

A description will now be given, with
reference to Fig. 4, of a microphone array apparatus
according to a first embodiment of the present
20   invention. The apparatus shown in Fig. 4 is made up
of n microphones 1-1 - 1-n forming a microphone array,
filters 2-1 - 2-n, an adder 3, a filter coefficient
calculator 4, a speaker (target sound source) 5, and a
speaker (noise source). The speech of the speaker 5
25   is input to the microphones 1-1 - 1-n, which converts
the received acoustic signals into electric signals,
which pass through the filters 2-1 - 2-n and are then
applied to the adder 3. The output signal of the
adder 3 is then to a remote terminal via a network or
30   the like. A speech signal from the remote side is
applied to the speaker 6, which is thus driven to
reproduce the original speech. Hence, the speaker 5
communicates with the other-side speaker. The
reproduced speech is input to the microphones 1-1 - 1-
35   n, and thus functions as noise to the speech of the
speaker 5. Hence, the speaker 6 is a noise source
with respect to the target sound source.

1   The filter coefficient calculator 4 is
supplied with the output signals of the microphones 1-
1 - 1-n, a noise (an input signal for driving the
speaker serving as noise source), and the output
5   signal (residual signal) of the adder 3, and thus
updates the coefficients of the filters 2-1 - 2-n. In
this case, the microphone 1-1 is handled as a
reference microphone. The subtracter 3 subtracts the
output signals of the filters 2-2 - 2-n from the
10   output signal of the filter 2-1.

Each of the filters 2-1 - 2-n can be
configured as shown in Fig. 5. Each filter includes
z^{-1} delay units 11-1 - 11-r-1, coefficient units 12-1.
- 12-r for multiplication of filter coefficients cp1,
15   cp2, ..., cpr, and adders 13 and 14. A symbol "r"
denotes the order of the filter.

When the signal from the noise source
(speaker 6) is denoted as xp(i) and the signal from
the target sound source (speaker 5) is denoted as
20   yp(i) (where i denotes the sample number and p is
equal to 1, 2, ..., n), the values fp(i) of the
memories of the filters 2-1 - 2-n (the input signals
to the filters and the output signals of the delay
units 11-1 - 11-r-1) are defined as follows:

25

$$fp(i) = xp(i) + yp(i) \qquad\qquad (8)$$

The output signal e of the adder in the echo
canceller using the conventional microphone array is
30   as follows:

$$e = \begin{bmatrix} f1(1) \cdot & \cdots f1(r) \end{bmatrix} \begin{bmatrix} c11 \\ c12 \\ \vdots \\ c1r \end{bmatrix}$$

35

$$-\sum_{i=2}^{n} \begin{bmatrix} fi(1) \cdot & \cdot & \cdot fi(r) \end{bmatrix} \begin{bmatrix} ci1 \\ ci2 \\ \vdots \\ cir \end{bmatrix} \qquad \cdots (9)$$

where f1(1), f1(2), ..., f1(r), ..., fi(1), fi(2), ..., fi(r) denote the values of the memories of the filters. The adder subtracts the output signals of the filters other than the reference filter from the output signal of the reference filter.

In contrast, the present invention controls the signals xp(i) in phase and performs the convolutional operation. The output signal e' of the adder thus obtained is as follows:

$$e' = [f1(1)' \cdots f1(r)']\begin{bmatrix} c11 \\ c12 \\ \vdots \\ c1r \end{bmatrix}$$

$$- \sum_{i=2}^{n} [fi(1)' \cdots fi(r)']\begin{bmatrix} ci1 \\ ci2 \\ \vdots \\ cir \end{bmatrix} \quad \cdots (10)$$

$$[fp(1)' \cdots fp(r)']$$
$$= [x(1)(p) \cdots x(q)(p)]\begin{bmatrix} fp(1) \cdots fp(r) \\ fp(2) \cdots fp(r+1) \\ \vdots \\ fp(q) \cdots fp(q+r-1) \end{bmatrix}$$
$$\cdots (11)$$

where (p) in x(1)(p), ..., x(q)(p) denotes signals from the noise source obtained when the microphones 1-1 - 1-n are in phase, and the symbol "q" denotes the number of samples on which the convolutional operation is executed.

When the signals xp(i) from the noise source and the signals yp(i) of the target sound source are concurrently input, that is, when the speaker 5 speaks at the same time as the speaker 6 outputs a reproduced speech, there is a small crosscorrelation therebetween because the coexisting speeches are uttered by different speakers. Hence, the equation (11) can be rewritten as follows:

1

$$
[fp(1)' \ \cdot \ \cdot \ \cdot \ fp(r)' \ ]
$$

$$
= [x(1)(p) \ \cdot \ \cdot \ \cdot \ x(q)(p)] \begin{bmatrix} fp(1) \cdot \ \cdot \ \cdot \ fp(r) \\ fp(2) \cdot \ \cdot \ \cdot \ fp(r+1) \\ \vdots \\ fp(q) \ \cdot \ \cdot \ \cdot \ fp(q+r-1) \end{bmatrix}
$$

$$
= [x(1)(p) \ \cdot \ \cdot \ \cdot \ x(q)(p)] \begin{bmatrix} \{xp(1)+yp(1)\} \cdots \{xp(r)+yp(r)\} \\ \{xp(2)+yp(2)\} \cdots \{xp(r+1)+yp(r+1)\} \\ \vdots \\ \{xp(q)+yp(q)\} \cdots \\ \qquad \{xp(q+r-1)+yp(q+r-1)\} \end{bmatrix}
$$

$$
\fallingdotseq \left[\sum_{i=1}^{q} x(i)(p) * xp(i) \ \cdot \ \cdot \ \cdot \ \sum_{i=1}^{q} x(i)(q) * xp(r+i-1) \right]
$$

$$
\cdots (12)
$$

15   It can be seen from the above equation (12),
an influence of the signals $yp(i)$ from the target
sound source to $[fp(1)', \ldots, fp(r)']$ is reduced. The
signal e' in the equation (10) is obtained by using
the equation (12), and then, an evaluation function J
20 $= (e')^2$ is calculated based on the obtained signal e'.
Then, based on the evaluation function $J = (e')^2$, the
filter coefficients of the filters 2-1 - 2-n are
updated.   That is, even in the state in which speeches
from the speaker (target sound source) 5 and the
25 speaker (noise source) 6 are concurrently applied to
the microphones 1-1 - 1-n, the noise contained in the
output signals of the microphones 1-1 - 1-n has a
large crosscorrelation to the input signal applied to
the filter coefficient calculator 4 and used to drive
30 the speaker 6, while having a small crosscorrelation
to the target sound source 5.   Hence, the filter
coefficients can be updated in accordance with the
evaluation function $J = (e')^2$. Hence, the output
signal of the adder 3 is the speech signal of the
35 speaker 5 in which the noise is suppressed.

        Fig. 6 is a block diagram of a microphone
array apparatus according to a second embodiment of

1   the present invention in which parts that are the same
       as those shown in the previously described figures are
       given the same reference numbers. The structure shown
       in Fig. 6 includes delay units 8-1 - 8-n (z^{-d1} - z^-
5   dn), and a delay calculator 9.
              The updating of the filter coefficients
       according to the second embodiment of the present
       invention is based on the following. The delay
       calculator 9 calculates the number of delayed samples
10   in each of the delay units 81-1 - 8-n so that the
       output signals of the microphones 1-1 - 1-n are pulled
       in phase. Further, the filter coefficient calculator
       4 calculates the filter coefficients of the filters 2-
       1 - 2-n. The delay calculator 9 is supplied with the
15   output signals of the microphones 1-1 - 1-n, and the
       input signal (noise) for driving the speaker 6. The
       filter coefficient calculator 4 is supplied with the
       output signals of the delay units 8-1 - 8-n, the
       output signal of the adder 3 and the input signal
20   (noise) for driving the speaker 6.
              When the output signals of the microphones
       1-1 - 1-n are denoted as gp(i) where p = 1, 2, ..., n;
       j is the sample number, a crosscorrelation function
       Rp(i) to the signals x(j) from the noise source is as
25   follows:

$$Rp(i) = \Sigma^{S}_{j=1} gp(j+i)*x(j) \qquad\qquad (13)$$

       where $\Sigma^{S}_{j=1}$ denotes a summation from j=1 to j=s, and s
30   denotes the number of samples on which the
       convolutional operation is executed. The number s of
       samples may be equal to tens to hundreds of samples.
       When a symbol "D" denotes the maximum delayed sample
       corresponding to the distances between the noise
35   source and the microphones, the term "i" in the
       equation (13) is such that i = 0, 1, 2, ..., D.
              For example, when the maximum distance

1   between the noise source and the furthest microphone is equal to 50 cm, and the sampling frequency is equal to 8 kHz, the speed of sound is approximately equal to 340 m/s, and thus the maximum number D of delayed

5   samples is as follows:

$$D = (\text{sampling frequency})*(\text{maximum distance}$$
$$\text{between the noise source and}$$
$$\text{microphone})/(\text{speed of sound})$$
10     $$=8000*(50/34000) = 11.76 \doteqdot 12.$$

Hence, the symbol "i" is equal to 1, 2, ..., 12. When the maximum distance between the noise source and the microphone is equal to 1m, the maximum number D of

15   delayed samples is equal to 24.

The value i_p (p = 1, 2, ..., n) is obtained which is the value of i obtained when the absolute value of the crosscorrelation function value $R_p(i)$ obtained by equation (13). Further, the maximum value

20   imax of the i_p is obtained. The above process is comprised of steps (A1) - (A11) shown in Fig. 7. The term imax is set to an initial value (equal to, for example, 0) and the variable p is set equal to 1, at step A1. At step A2, the term Rpmax is set to an

25   initial value (equal to, for example, 0.0), and the term i_p is set to an initial value (equal to, for example, 0). Further, at step A2, the variable i is set equal to 0. At step A3, the crosscorrelation function value $R_p(i)$ defined by the equation (13) is

30   obtained.

At step A4, it is determined whether the crosscorrelation function value $R_p(i)$ is greater than the term Rpmax. If the answer is YES, the $R_p(i)$ obtained at that time is set to Rpmax at step A5. If

35   the answer is NO, the variable i is incremented by 1 (i = i + 1) at step A6. At step A7, it is determined whether $i \le D$. If the value i is equal to or smaller

than the maximum number D of delayed samples, the process returns to step A3. If the value i exceeds the maximum number D of delayed samples, the process proceeds with step A8. At step A8, it is determined that the value ip is greater than the value imax. If the answer is YES, the value ip obtained at that time is set to imax at step A9. If the answer is NO, the variable p is incremented by 1 (p = p + 1) at step A10. At step A11 it is determined whether $p \leq n$. If the answer of step A11 is YES, the process returns to step A2. If the answer is NO, the retrieval of the crosscorrelation function value $Rp(i)$ ends, so that the maximum value imax of the IP within the range of i $\leq$ D.

The number dp of delayed samples of the delay unit can be obtained as follows by using the terms ip and imax obtained by the above maximum value detection:

$$dp = imax - ip \qquad (14)$$

Hence, the numbers di - dn of delayed samples of the delay units 8-1 - 8-n can be set by the delay calculator 9.

The filters 2-1 - 2-n can be configured as shown in Fig. 5. When the output signals of the filters 2-1 - 2-n are denoted as outp (p = 1, 2, ..., n) defined by the following:

$$outp = \Sigma^n_{i=1} cpi * fp(i) \qquad (15)$$

where $\Sigma^n_{i=1}$ denotes a summation from i=1 to i=n, cpi denotes the filter coefficients, and fp(i) denotes the values of the memories of the filters and are also input signals applied to the filters.

The filter coefficient calculator 4 calculates the crosscorrelation between the present

and past input signals of the filters 2-1 - 2-n and the signals form the noise source, and thus updates the filler coefficients. The crosscorrelation function value fp(i)' is written as follows:

$$fp(i)' = \Sigma^q_{n=1} x(j) * fp(i+j-1) \tag{16}$$

where $\Sigma^q_{n=1}$ denotes a summation from j=1 to J=q, and the symbol q denotes the number of samples on which the convolutional operation is carried out in order to calculate the crosscorrelation function value and is normally equal to tens to hundreds of samples.

By using the above crosscorrelation function value fp(i)', the output signal e' of the adder 3 is obtained as follows:

$$e' = \Sigma^r_{j=1}[f1(j)' * c1j] - \Sigma^n_{j=1}[fi(j)' * cij] \tag{17}$$

The above operation is the convolutional operation and can be thus implemented by a digital signal processor (DSP). In this case, the adder 3 subtracts the output signals of the microphones 1-2 - 1-n obtained via the filters 2-2 - 2-n from the output signal of the reference microphone 1-1 obtained via the filter 2-1.

The evaluation function is defined so that J = (e')^2 where the output signal e' of the adder 3 is handled as an error signal. By using the evaluation function J = (e')^2, the filter coefficients are obtained. For example, the filter coefficients can be obtained by the steepest descent method. By using the following expressions, the filter coefficients c11, c12, ..., cn1, cn2, ..., cnr can be obtained as follows:

1

$$\begin{bmatrix} c11 \\ c12 \\ \vdots \\ c1r \end{bmatrix} = \begin{bmatrix} c11_{old} \\ c12_{old} \\ \vdots \\ c1r_{old} \end{bmatrix} - t1 * \begin{bmatrix} f1(1)' \\ f1(2)' \\ \vdots \\ f1(r)' \end{bmatrix} \qquad \cdots (18)$$

5

$$t1 = \alpha * (e' / f1_{norm})$$

$$\begin{bmatrix} cp1 \\ cp2 \\ \vdots \\ cpr \end{bmatrix} = \begin{bmatrix} cp1_{old} \\ cp2_{old} \\ \vdots \\ cpr_{old} \end{bmatrix} + tp * \begin{bmatrix} fp(1)' \\ fp(2)' \\ \vdots \\ fp(r)' \end{bmatrix} \qquad \cdots (19)$$

10

$$tp = \alpha * (e' / fp_{norm})$$
$$p = 2, 3, \cdots n$$

where the norm fp_{norm} corresponds to the aforementioned formula (3) and can be written as

15   follows:

$$fp_{norm} = [(fp(1)')^2 + (fp(2)')^2 + \cdots + (fp(r)')^2]^{1/2} \qquad (20)$$

20   The term α in the equations (18) and (19) is a constant as has been described previously, and represents the speed and precision of convergence of the filter coefficients towards the optimal values.

Hence, the output signal e' of the adder 3

25   is obtained as follows:

$$e' = out1 - \Sigma^n_{i=2} outi \qquad (21)$$

The delay units 8-1 - 8-n change the phases of the

30   input signals applied to the filters 2-1 - 2-n. Hence, the filter coefficients can easily be updated by the filter coefficient calculator 4. Even under a situation such that the speaker 5 speaks at the same time as a sound is emitted from the speaker 6, the

35   updating of the filter coefficients can be realized. Hence, it is possible to definitely suppress the noise components that enter the microphones 1-1 - 1-n from

1   the speaker 6 which serves as a noise source.

        Fig. 8 is a block diagram of a third embodiment of the present invention, in which parts that are the same as those shown in Fig. 4 are given

5   the same reference numbers. In Fig. 8, there are a noise source 16 and a supplementary microphone 21. The supplementary microphone 21 can have the same structure as that of the microphones 1-1 - 1-n forming the microphone array.

10   The structure shown in Fig. 8 differs from that shown in Fig. 4 in that the output signal of the supplementary microphone 21 can be input to the filter coefficient calculator 4 as a signal from the noise source. Hence, even in a case where the noise source

15   16 is an arbitrary noise source other than the speaker, such as an air conditioning system, the noise can be suppressed by using the evaluation function $J = (e')^2$ used to update the filter coefficients, as has been described with reference to Fig. 4.

20   Fig. 9 is a block diagram of a fourth embodiment of the present invention, in which parts that are the same as those shown in Figs. 6 and 7 are given the same reference numbers. The structure shown in Fig. 9 is almost the same as that shown in Fig. 6

25   except that the output signal of the supplementary microphone 21 is applied, as the signal from a noise source, to the delay calculator 9 and the filter coefficient calculator 4. Hence, as in the case of the structure shown in Fig. 6, the numbers of delayed

30   samples of the delay units 2-1 - 2-n are controlled by the delay calculator 9, and the filter coefficients of the filters 2-1 - 2-n are updated by the filter coefficient calculator 4. Hence, noise can be compressed.

35   Fig. 10 is a block diagram of a low-pass filter used in the filter coefficient updating process used in the embodiments of the present invention. The

1   low-pass filter shown in Fig. 10 includes coefficient
    units 22 and 23, an adder 24 and a delay unit 25. The
    structure shown in Fig. 10 is directed to calculating
    the aforementioned crosscorrelation function value
5   fp(i)' in which the coefficient unit 23 has a filter
    coefficient β and the coefficient unit 22 has a filter
    coefficient (1-β). The value fp(i)' is obtained as
    follows:

10              $$fp(i)' = \beta * fp(i)'_{old} + (1-\beta) * [x(1) * fp(i)] \quad (22)$$

    where the coefficient β is set so as to satisfy 0.0 <
    β < 1.0 and $fp(i)'_{old}$ denotes the value of a memory
    (delay unit 25) of the low-pass filter.
15   The low-pass filter shown in Fig. 10 is a
    cyclic type low-pass filter, in which weighting for
    the past signals is made comparatively light in order
    to prevent the convolutional operation from outputting
    an excessive output value and thus stably obtain the
20 crosscorrelation function value fp(i)'.
              Fig. 11 is a block diagram of a structure
    directed to implementing the embodiments of the
    present invention by using a digital signal processor
    (DSP). Referring to Fig. 11, there are provided the
25 microphones 1-1 - 1-n forming a microphone array, a
    DSP 30, low-pass filters (LPF) 31-1 - 31-n, analog-to-
    digital (A/D) converters 32-1 - 32-n, a digital-to-
    analog (D/A) converter 33, a low-pass filter (LPF) 34,
    an amplifier 35 and a speaker 36.
30   The aforementioned filters 2-1 - 2-n and the
    filter coefficient calculator 4 used in the structure
    shown in Fig. 4 and the filters 2-1 - 2-n, the filter
    coefficient calculator 4 and the delay units 8-1 - 8-n
    used in the structure shown in Fig. 6 can be realized
35 by the combinations of a repetitive process, a sum-of-
    product operation and a condition branching process.
    Hence, the above processes can be implemented by

1   operating functions of the DSP 30.

The low-pass filters 31-1 - 31-n function to
eliminate signal components located outside the speech
band. The A/D converters 32-1 - 32-n converts the
5   output signals of the microphones 1-1 - 1-n obtained
via the low-pass filters 31-1 - 31-n into digital
signals and have a sampling frequency of, for example,
8 kHz. The digital signals have the number of bits
which corresponds to the number of bits processed in
10   the DSP 30. For example, the digital signals consists
of 8 bits or 16 bits.

An input signal obtained via a network or
the like is converted into an analog signal by the D/A
converter 33. The analog signal thus obtained passes
15   through the low-pass filter 34, and is then applied to
the amplifier 35. An amplified signal drives the
speaker 36. The reproduced sound emitted from the
speaker 36 serves as noise with respect to the
microphones 1-1 - 1-n. However, as has been described
20   previously, the noise can be suppressed by updating
the filter coefficients by the DSP 30.

Fig. 12 is a block diagram showing functions
of the DSP that can be used in the embodiments of the
present invention. In Fig. 12, parts that are the
25   same as those shown in the previously described
figures are given the same reference numbers. In Fig.
12, the low-pass filters 31-1 - 31-n and 34, the A/D
converters 32-1 - 32-n, the D/A converter 33 and the
amplifier 35 shown in Fig. 11 are omitted. The filer
30   coefficient calculator 4 includes a crosscorrelation
calculator 41 and a filter coefficient updating unit
42. The delay calculator 9 includes a
crosscorrelation calculator 43, a maximum value
detector 44 and a number-of-delayed-samples calculator
35   45.

The crosscorrelation calculator 43 of the
delay calculator 9 receives the output signals gp(j9

1　　of the microphones 1-1 - 1-n and the drive signal for
the speaker 36 (which functions as a noise source),
and calculates the crosscorrelation function value
$Rp(i)$ defined in formula (13). The maximum value

5　　detector 44 detects the maximum value of the
crosscorrelation function value $Rp(i)$ in accordance
with the flowchart of Fig. 7. The number-of-delayed-
samples calculator 45 obtain the numbers dp of delayed
samples of the delay units 8-1 - 8-n by using the ip

10　　and imax obtained during the maximum value detecting
process. The numbers of delayed samples thus obtained
are then set in the delay units 8-1 - 8-n.
　　　　The crosscorrelation calculator 41 of the
filter coefficient calculator 4 receives the signals

15　　from the noise source delayed so that these signals
are in phase by the delay units 8-1 - 8-n, the drive
signal for the speaker 36 serving as a noise source,
and the output signal of the adder 3, and calculates
the crosscorrelation function value $fp(i)'$ in

20　　accordance with equation (16). In the process of
calculating the crosscorrelation function value
$fp(i)'$, the low-pass filtering process shown in Fig.
10 can be included. The filter coefficient updating
unit 42 calculates the filter coefficients cpr in

25　　accordance with the equations (17), (18) and (19), and
thus the filter coefficients of the filters 2-1 - 2-n
shown in Fig. 5 can be updated.
　　　　Fig. 13 is a block diagram of a structure of
the delay units. Each delay unit includes a memory

30　　46, a write controller 47, and a read controller 49,
which controllers are controlled by the delay
calculator 9. The delay unit shown in Fig. 13 is
implemented by an internal memory built in the DSP.
The memory 46 has an area corresponding to the maximum

35　　value D of delayed samples. The write operation is
performed under the control of the write controller
47, and the read operation is performed under the

1   control of the read controller 48. A write pointer WP
     and a read pointer RP are set at intervals equal to
     the number dp of delayed samples calculated by the
     calculator 9. Further, the write pointer WP and the
5   read pointer RP are shifted in the directions
     indicated by arrows of broken lines at every
     write/read timing. Hence, the signal written into the
     address indicated by the write pointer WP is read when
     it is indicated by the read pointer RP after the
10   number dp of delayed samples.

          Fig. 14 is a block diagram of a fifth
     embodiment of the present invention, which includes
     microphones 51-1 and 51-2 forming a microphone array,
     linear predictive filters 52-1 and 52-2, liner
15   predictive analysis units 53-1 and 53-2, a sound
     source position detector 54 and a sound source 55 such
     as a speaker. Although a plurality of microphones
     more than two can be used to form a microphone array,
     the structure uses only two microphones 51-1 and 51-2
20   for the sake of simplicity.

          The output signals a(j) and b(j) of the
     microphones 51-1 and 51-2 are applied to the linear
     predictive analysis units 53-1 and 53-2 and the linear
     predictive filters 52-1 and 52-2. Then, the linear
25   predictive analysis units 53-1 and 53-2 obtain
     autocorrelation function value and thus calculate
     linear predictive coefficients, which are used to
     update the filter coefficients of the linear
     predictive filters 52-1 and 52-2. Then, the position
30   of the sound source 55 is detected by the sound source
     detector 54 by using a linear predictive residual
     signal which is the difference between the output
     signals of the linear predictive filters 52-1 and 52-
     2. Finally, information concerning the position of
35   the sound source is output.

          Fig. 15 is a block diagram of the internal
     structures of the blocks shown in Fig. 14. Referring

to Fig. 15, there are illustrated autocorrelation function value calculators 56-1 and 56-2, linear predictive coefficient calculators 57-1 and 57-2, a crosscorrelation coefficient calculator 58, and a position detection processing unit 59. The linear predictive analysis units 53-1 and 53-2 include the autocorrelation function value calculators 56-1 and 56-2, and the linear predictive coefficient calculators 57-1 and 57-2, respectively. The output signals a(j) and b(j) of the microphones 51-1 and 51-2 are respectively input to the autocorrelation function value calculators 56-1 and 56-2.

The autocorrelation function value calculator 56-1 of the linear predictive analysis unit 53-1 calculates the autocorrelation function value Ra(i) by using the output signal a(i) of the microphone 51-1 and the following formula:

$$Ra(i) = \Sigma^n_{j=1}a(j)*a(j+i) \qquad (23)$$

where $\Sigma^n_{j=1}$ denotes a summation of j=1 to j=n, and the symbol n denotes the number of samples on which the convolutional operation is carried out and is generally equal to a few of hundreds. When the symbol q denotes the order of the linear predictive filter, then $0 \leq i \leq q$.

The linear predictive coefficient calculator 57-1 calculates the linear predictive coefficients $\alpha a1, \alpha a2, ..., \alpha aq$ on the basis of the autocorrelation function value Ra(i). The linear predictive coefficients can be obtained any of various known methods such as an autocorrelation method, a partial correlation method and a covariance method. Hence, the linear predictive coefficients can be implemented by the operational functions of the DSP.

In the linear predictive analysis unit 53-2 corresponding to the microphone 51-2, the

autocorrelation function value calculator 56-2
calculates the autocorrelation function value Rb(i) by
using the output signal b(j) of the microphone 51-2 in
the same manner as the formula (23). The linear
predictive coefficient calculator 57-2 calculates the
linear predictive coefficients $ab1$, $ab2$, ..., abq.

The linear predictive filters 52-1 and 52-2
may have an qth-order FIR filter. Hence, the filter
coefficients $c1$, $c2$, ..., cq are respectively updated
by the linear predictive coefficients $aa1$, $aa2$, ...,
aaq, $ab1$, $ab2$, ..., abq. The filter order q of the
linear predictive filters 52-1 and 52-2 is defined by
the following expression:

$$q = [(sampling\ frequency)*(intermicrophone\ distance)]/(speed\ of\ sound) \qquad (24)$$

The high-hand side of the formula (24) is the same as
that of the aforementioned formula (7).

The source position detector 54 includes the
crosscorrelation coefficient calculator 58 and the
position detection processing unit 59. The
crosscorrelation coefficient calculator 58 calculates
the crosscorrelation coefficient $r'(i)$ by using the
output signals of the linear predictive filters 52-1
and 52-2, that is, the linear predictive residual
signals $a'(j)$ and $b'(j)$ for the output signals $a(j)$
and $b(j)$ of the microphones 51-1 and 51-2. In this
case, the variable i meets $-q \le i \le q$.

The position detection processing unit 59
obtains the value of i at which the crosscorrelation
coefficient $r'(i)$ is maximized, and outputs sound
source position information indicative of the position
of the sound source 55. The relation between the
sound source position and the imax is as shown in Fig.
16. When imax = 0, the sound source 55 is located in
front of or at the back of the microphones 51-1 and

1   51-2, and is spaced apart from the microphones 51-1
and 51-2 by an even distance. When imax = q, the
sound source 55 is located on an imaginary line
connecting the microphones 51-1 and 51-2 and is closer
5   to the microphone 51-1. When imax = -q, the sound
source 55 is located on an imaginary line connecting
the microphones 51-1 and 51-2 and is closer to the
microphone 51-2. If three or more microphones are
used, it is possible to detect the position of the
10   sound source including information indicating the
distances to the sound source.

Generally, the speech signal has a
comparatively large autocorrelation function value.
The prior art directed to obtaining the
15   crosscorrelation function r(i) using the output
signals a(j) and b(j) of the microphones 51-1 and 51-2
cannot easily detect the position of the sound source
because the crosscorrelation coefficient r(i) does not
change greatly as a function of the variable i. In
20   contrast, according to the embodiments of the present
invention, the position of the sound source can be
easily detected even for a large autocorrelation
function value because the crosscorrelation
coefficient r'(i) is obtained by using the linear
25   predictive residual signals.

Fig. 17 is a block diagram of a sixth
embodiment of the present invention, in which parts
that are the same as those shown in Fig. 14 are given
the same reference numbers. Referring to Fig. 17,
30   there are illustrated a linear predictive analysis
unit 53A and a speaker 55A serving as a sound source.l
A drive signal for the speaker 55A is applied to the
linear predictive analysis unit 53A, which analyzes
the signal of the sound source in the linear
35   predictive manner, and thus obtain the linear
predictive coefficients. The linear predictive
analysis unit 53 is provided in common to the linear

1   predictive filters 52-1 and 52-2. The linear predictive residual signals for the output signals a(j) and b(j) of the microphones 51-1 and 51-2 are obtained. The sound source position detecting unit 54

5   obtains the crosscorrelation coefficient r'(i) by using the obtained linear predictive residual signals. Hence, the position of the sound source can be identified.

        Fig. 18 is a block diagram of a seventh

10   embodiment of the present invention. Referring to Fig. 18, there are illustrated microphones 61-1 and 61-2 forming a microphone array, a signal estimator 62, a synchronous adder 63, and a sound source 65. The synchronous adder 63 performs a synchronous

15   addition operation on the output signals of the microphones 61-1 and 61-2 assuming that microphones 64-1, 64-2, ... are present at estimated positions depicted by the broken lines, these estimated positions being located on an imaginary line

20   connecting the microphones 61-1 and 61-2 together.

        Fig. 19 is a block diagram of the detail of the seventh embodiment of the present invention, in which parts that are the same as those shown in Fig. 18 are given the same reference numbers. There are

25   provided a particle velocity calculator 66, an estimation processing unit 67, delay units 68-1, 68-2, ..., and an adder 69. Fig. 19 shows a case where the sound source 65 is located at an angle θ with respect to the imaginary line connecting the

30   microphones 61-1 and 61-2 forming the microphone array. The process is carried out under an assumption that the microphones 64-1, 64-2, ... are arranged on the imaginary line as depicted by the symbols of broken lines.

35   The signal estimator 62 includes the particle velocity calculator 66 and the estimation processing unit 67. A propagation of the acoustic

wave from the sound source 65 can be expressed by the
wave equation as follows:

$$-\partial V/\partial x = (1/K)(\partial P)/\partial t$$
$$-\partial P/\partial t = \sigma(\partial V/\partial t) \tag{25}$$

where P is the sound pressure, V is the particle
velocity, K is the bulk modulus, and σ is the density
of a medium.

The particle velocity calculator 66
calculates the velocity of particles from the
difference between a sound pressure P(j, 0)
corresponding to the amplitude of the output signal
a(j) of the microphone 61-1 and a sound pressure P(j,
1) corresponding to the amplitude of the output signal
b(j) of the microphone 61-2. That is, the velocity
V(j+1, 0) of particles at the microphone 61-1 is as
follows:

$$V(j+1,0) = V(j,0)+[P(j,1)-P(j,0)] \tag{26}$$

where j is the sample number.

The estimation processing unit 67 obtains
estimated positions of the microphones 64-1, 64-2, ...
by the following equations:

$$P(j,x+1) = P(j,x)+\beta(x)[V(j+1,x)-V(j,x)]$$
$$V(J+1,x) = V(j+1,x-1)+[P(j,x-1)-p(j,x)] \tag{27}$$

where x denotes an estimated position and $\beta(x)$ is an
estimation coefficient.

If the positions of the microphones 61-2 and
61-1 are described so that x = 1 and x = 0,
respectively, the microphones 64-1 and 64-2 are
respectively located at estimated positions of x = 2
and x = 3. The estimation processing unit 62
supplies, by using the two microphones 61-1 and 61-2,

1   the synchronous adder 63 with the output signals of
     the microphones 64-1, 64-2, ..., as if these
     microphones 64-1, 64-2, ... are actually arranged.
     Hence, even the microphone array formed by only the
5   two microphones 61-1 and 61-2 can emphasize the target
     sound by the synchronous adding operation as if a
     large number of microphones is arranged.

          The synchronous adder 63 includes the delay
     units 68-1, 68-2, ..., and the adder 69. When the
10   number of delayed samples is denoted as d, the delay
     units 68-1, 68-2, ... can be described as z^{-d}, z^{-2d},
     z^{-3d}, ... The number d of delayed samples is
     calculated as follows by using the angle θ with
     respect to the imaginary line connecting the
15   microphones 61-1 and 61-2 together obtained by the
     aforementioned manner:

          d = [(number of sampling frequency)*
               (intermichrophone distance)*cosθ]/
20   (velocity of sound)   (28)

          Hence, the output signals of the microphones
     61-1 and 61-2 and the output signals of the
     microphones 64-1, 64-2, ... located at estimated
25   positions are pulled in phase by the delay units 68-1,
     68-2, ..., and are then added by the adder 69. Hence,
     the target sound can be emphasized by the synchronous
     addition operation. With the above arrangement, the
     target sound can be emphasized so as to have a power
30   obtained by a small number of actual microphones and
     the estimated microphones.

          Fig. 20 is a block diagram of an eighth
     embodiment of the present invention in which parts
     that are the same as those shown in Fig. 18 are given
35   the same reference numbers. Provided are a reference
     microphone 71, a subtracter 72, a weighting filter 73
     and an estimation coefficient decision unit 74. In

1   the eight embodiment of the present invention, the
reference microphone 71 is arranged at a position of x
= 2 so as to have the same intervals as those at which
the microphone 61-1 and the microphone 61-2 are
5   located at positions of x = 0 and x = 1. An estimated
position error is obtained by the subtracter 72. The
weighting filter 73 processes the estimated position
error so as to have an acoustic sense characteristic.
Then, the estimation coefficient decision unit 74
10   determines the estimation coefficient $\beta(x)$.

More particularly, the subtracter 72
calculates an estimation error $e(j)$ which is the
difference between the estimated signal $(j,2)$ of the
microphone 64-1 located at x = 2 and the output signal
15   $ref(j)$ of the reference microphone 71 by the following
formula:

$$e(j) = P(j,2)-ref(j)$$
$$= P(j,1)+\beta(2)[V(j+1,1)-V(j,1)]-ref(j)$$

20   (29)

The estimation coefficient decision unit 74
can determine the estimation coefficient $\beta(2)$ so that
the average power of the estimation error $e(j)$ can be
25   minimized. That is, the estimation processing unit 62
(shown in Fig. 18 or Fig. 19) performs an estimation
process for the output signals of the estimated
microphones 64-1, 64-2, ... by using the estimation
coefficient $\beta(2)$ with x = 2, 3, 4, ..., and outputs
30   the operation result.

The weighting filter 73 weights the
estimation error $e(j)$ in accordance with the acoustic
sense characteristic, which is known a loudness
characteristic in which sensitivity obtained around 4
35   kHz is comparatively high. More particularly, a
comparatively large weight is given to frequency
components of the estimation error $e(j)$ around 4 kHz.

1   Hence, even in the process for the estimated
microphones located at $x = 2, 3, \ldots,$ the estimation
error can be reduced in the band having comparatively
high sensitivity, and the target sound can be
5   emphasized by the synchronous adding operation.

Fig. 21 is a block diagram of a ninth
embodiment of the present invention. The structure
shown in Fig. 21 includes the microphones 61-1 and 61-
2 forming a microphone array, signal estimators 62-1,
10   62-2, $\ldots,$ 62-s, synchronous adders 63-1, 63-2, $\ldots,$
63-n, estimated microphones 64-1, 64-2, $\ldots,$ the sound
source 65, and a sound source position detector 80.

The angles $\theta_0, \theta_1, \ldots, \theta_s$ are defined with
respect to the microphone array of the microphones 61-
15   1 and 61-2, and the signal estimators 62-1 - 62-s and
the synchronous adders 63-1 - 63-s are provided to the
respective angles. The signal estimators 62-1 - 62-s
obtain estimated coefficients $\beta(x, \theta)$ beforehand. For
example, as shown in Fig. 20, the reference microphone
20   71 is provided to obtain the estimated coefficient
$\beta(x, \theta)$.

The synchronous adders 63-1 - 63-s pull the
output signals of the signal estimators 62-1 - 62-s in
phase, and add these signals. Hence, the output
25   signals corresponding to the angles $\theta_0 - \theta_s$ can be
obtained. The sound source position detector 80
compares the output signals of the synchronous adders
63-1 - 63-s with each other, and determines that the
angle at which the maximum power can be obtained is
30   the direction in which the sound source 65 is located.
Then, the detector 80 outputs information indicating
the position of the sound source. Further, the
detector 80 can output the signal having the maximum
power as the emphasized target signal.
35   Fig. 22 is a block diagram of a tenth
embodiment of the present invention, which includes a
camera such as a video camera or a digital camera,

1   microphones 91-1 and 91-2 forming a microphone array,
a sound source detector 92, a face position detector
93, an integrate decision processing unit 94 and a
sound source 95.

5   The microphones 91-1 and 91-2 and the sound
source position detector 92 is any of those used in
the aforementioned embodiments of the present
invention. The information concerning the position of
the sound source 95 is applied to the integrate

10   decision processing unit 94 by the sound source
position detector 92. The position of the face of the
speaker is detected from an image of the speaker taken
by the camera 90. For example, a template matching
method using face templates may be used. An

15   alternative method is to extract an area having skin
color from a color video signal. The integrate
decision processing unit 94 detects the position of
the sound source 95 based on the position information
from the sound source position detector 92 and the

20   position detection information from the face position
detector 93.

        For example, a plurality of angles $\theta_0 - \theta_s$
are defined with respect to the imaginary line
connecting the microphones 91-1 and 91-2 and the

25   picture taking direction of the camera 90. Then,
position information inf-A(θ) indicating the
probability of the direction in which the sound source
95 may be located is obtained by a sound source
position detecting method for calculating the

30   crosscorrelation coefficient based on the linear
predictive errors of the output signals of the
microphones 91-1 and 91-2 or by another method using
the output signals of the real microphones 91-1 and
91-2 and estimated microphones located on the

35   imaginary line connecting the microphones 91-1 and 91-
2 together. Also, position information inf-V(θ)
indicating the probability of the direction in which

1   the face of the speaker may be located is obtained.
    Then, the integrate decision processing unit 94
    calculates the product res(θ) of the position
    information inf-A(θ) and inf-V(θ), and outputs the
5   angle θ at which the product res (θ) is maximized as
    sound source position information. Hence, it is
    possible to more precisely detect the direction in
    which the sound source 95 is located. It is also
    possible to obtain an enlarged image of the sound
10 source 95 by an automatic control of the camera such
    as a zoom-in mode.
            The present invention is not limited to the
    specifically disclosed embodiments, and variations and
    modifications may be made without departing from the
15 scope of the present invention. For example, any of
    the embodiments of the present invention can be
    combined for a specific purpose such as noise
    compression, target sound emphasis or sound source
    position detection. The target sound emphasis and the
20 sound source position detection may be applied to not
    only a speaking person but also a source emitting an
    acoustic wave.

25

30

35